

| EVENT | 4 LED products | | | Status | 2 LED products |
|--------------------------------|----------------|-------------|-------------|--------|-----------------|
| | Packet | Printer | | | |
| Packet arrived | 50 ms | | | | 50 ms |
| Printing | | ON | | | ON |
| Not printing | | OFF | | | |
| Printer Busy | | | 50ms/1s | | |
| Test button pressed | OFF | OFF | 0.1s/0.1s | | 0.1s/0.1s |
| Burn-in Mode | 80 ms/2 s | 80 ms/2 s | 80 ms/2 s | | 80 ms/2 s |
| Defaults Set | | | ON | | ON |
| Forced factory def. | ON | OFF | 0.3s/0.3s | | 0.3s/0.3s |
| Corrupt EEPROM | OFF | OFF | 0.3s/0.3s | | 0.3s/0.3s |
| EEPROM read failure | OFF | ON | 0.3s/0.3s | | 0.3s/0.3s |
| Missing EEPROM | OFF | 0.3s/0.3s | 0.3s/0.3s | | 0.3s/0.3s |
| Illegal serial no. | 0.3s/0.3s | 0.3s/0.3s | 0.3s/0.3s | | 0.3s/0.3s |
| Flash loading | | 0.5s/0.5s | | | |
| Flash loading failed | OFF | OFF | 0.3s/0.3s | | 0.3s/0.3s |
| Internal Error | 0.5s/0.8s | 0.25s/0.1s | 1s/1.25s | | 1s/1.25s |
| Token-Ring loopback failure | OFF | 0.15s/0.15 | 0.3s/0.3s | | 0.3s/0.3s |
| Token-Ring speed error | 0.3s/0.3s | OFF | ON | | ON |
| PROM/Flash checksum error | | | 0.25s/0.25s | | 3 long, 1 short |
| Bad RAM | | 0.25s/0.25s | 0.25s/0.25s | | 3 long, 2 short |
| Wrong product | | 0.25/0.75s | 0.25s/0.25s | | S.O.S |

// Last updated January 9, 1997 by JJ