

EVENT	4 LED products			Status	2 LED products
	Packet	Printer			
Packet arrived	50 ms				50 ms
Printing		ON			ON
Not printing		OFF			
Printer Busy			50ms/1s		
Test button pressed	OFF	OFF	0.1s/0.1s		0.1s/0.1s
Burn-in Mode	80 ms/2 s	80 ms/2 s	80 ms/2 s		80 ms/2 s
Defaults Set			ON		ON
Forced factory def.	ON	OFF	0.3s/0.3s		0.3s/0.3s
Corrupt EEPROM	OFF	OFF	0.3s/0.3s		0.3s/0.3s
EEPROM read failure	OFF	ON	0.3s/0.3s		0.3s/0.3s
Missing EEPROM	OFF	0.3s/0.3s	0.3s/0.3s		0.3s/0.3s
Illegal serial no.	0.3s/0.3s	0.3s/0.3s	0.3s/0.3s		0.3s/0.3s
Flash loading		0.5s/0.5s			
Flash loading failed	OFF	OFF	0.3s/0.3s		0.3s/0.3s
Internal Error	0.5s/0.8s	0.25s/0.1s	1s/1.25s		1s/1.25s
Token-Ring loopback failure	OFF	0.15s/0.15	0.3s/0.3s		0.3s/0.3s
Token-Ring speed error	0.3s/0.3s	OFF	ON		ON
PROM/Flash checksum error			0.25s/0.25s		3 long, 1 short
Bad RAM		0.25s/0.25s	0.25s/0.25s		3 long, 2 short
Wrong product		0.25/0.75s	0.25s/0.25s		S.O.S

// Last updated January 9, 1997 by JJ