

# AXIS Q6100-E Network Camera

For 360° real-time monitoring and great detail

With four 5 MP sensors, AXIS Q6100-E provides a complete 360° overview with great image usability day and night. Designed for use with any AXIS Q61 Series or AXIS Q63 Series camera, it enables one-click PTZ control and autopilot for automatic PTZ tracking within the viewing areas. Directional audio detection triggered by audio incidents redirects the PTZ camera to the audio source. Each sensor has exchangeable lenses with autofocus for maximum flexibility and accurate configuration. AXIS Camera Heater Power Supply is required when an AXIS Q63 Series is used.

- > 360° camera with one-click PTZ control
- > 4 x 5 MP sensors, total 20 MP resolution
- > Exchangeable and tiltable lenses
- > Requires an AXIS Q61 Series or AXIS Q63 Series camera
- > Directional audio detection included



# AXIS Q6100-E Network Camera

<b>Variants</b>	AXIS Q6100-E 50 Hz AXIS Q6100-E 60 Hz	Video: day-night mode, live stream open, tampering
<b>Camera</b>		<b>Event actions</b>
<b>Supported products</b>	AXIS Q61-E PTZ Network Cameras AXIS Q63-E PTZ Network Cameras	Record video: SD card and network share Upload of images or video clips: FTP, SFTP, HTTP, HTTPS, network share and email Pre- and post-alarm video or image buffering for recording or upload Notification: email, HTTP, HTTPS, TCP and SNMP trap PTZ: PTZ preset Overlay text, day/night mode, Status LED, WDR mode MQTT publish
<b>Image sensor</b>	4 x 5 MP progressive scan RGB CMOS 1/2.5"	<b>Data streaming</b>
<b>Lens</b>	Autofocus lenses, Fixed iris, F2.0, Focal length: 2.8 mm Horizontal field of view: 360° Vertical field of view: 84°	Event data
<b>Day and night</b>	Automatically removable infrared-cut filter	<b>Built-in installation aids</b>
<b>Minimum illumination</b>	Color: 0.4 lux at 50 IRE, F2.0 B/W: 0.03 lux at 50 IRE, F2.0	Installation focus, lens selection, positioning calibration, PTZ remote connection
<b>Shutter speed</b>	1/32500 to 1/20 s	<b>Cybersecurity</b>
<b>Camera adjustment</b>	Pan, tilt and rotate	<b>Edge security</b>
<b>Pan/Tilt/Zoom</b>	One-click PTZ control	Signed OS, brute force delay protection, digest authentication and OAuth 2.0 RFC6749 OpenID Authorization Code Flow for centralized ADFS account management, password protection, encrypted file system (AES-XTS-Plain64 256bit)
<b>System on chip (SoC)</b>		<b>Network security</b>
<b>Model</b>	S5	IEEE 802.1X (EAP-TLS, PEAP-MSCHAPv2), HTTPS/HSTS, TLS v1.2/v1.3, Network Time Security (NTS), X.509 Certificate PKI, host-based firewall
<b>Memory</b>	2048 MB RAM, 512 MB Flash	<b>Documentation</b>
<b>Video</b>		<i>AXIS OS Hardening Guide</i> <i>Axis Vulnerability Management Policy</i> <i>Axis Security Development Model</i> AXIS OS Software Bill of Material (SBOM) To download documents, go to <a href="https://axis.com/support/cybersecurity/resources">axis.com/support/cybersecurity/resources</a> To read more about Axis cybersecurity support, go to <a href="https://axis.com/cybersecurity">axis.com/cybersecurity</a>
<b>Video compression</b>	H.264 (MPEG-4 Part 10/AVC), Main and High Profiles H.265 (MPEG-H Part 2/HEVC), Main Profile	<b>General</b>
<b>Resolution</b>	4 x 2592x1944 to 320x240 Default: 2592x1944	<b>Casing</b>
<b>Frame rate</b>	Up to 20 fps (50/60 Hz) in all resolutions	IP66-, NEMA 4X- and IK10-rated Polycarbonate hardcoated dome Aluminum casing
<b>Video streaming</b>	Multiple, individually configurable streams in H.264 and H.265 Axis Zipstream technology in H.264 and H.265 Controllable frame rate and bandwidth VBR/ABR/MBR H.264/H.265	<b>Sustainability</b>
<b>Image settings</b>	Resolution, compression, saturation, brightness, sharpness, contrast, white balance, exposure level, exposure mode, shutter Et gain fine tuning of behavior at normal and low light, polygon privacy masks (maximum 8 per channel), WDR, dynamic text and image overlay	PVC free
<b>Signal-to-noise ratio</b>	>55 dB	<b>Power</b>
<b>Network</b>		<b>AXIS Q6100-E with Solo Kit (without a PTZ):</b> Power consumption: typical 9 W, max 23 W External power input 24 VDC: typical 8.6 W, max 75 W AXIS T8154: 100-240 VAC <b>AXIS Q6100-E with AXIS Q61-E PTZ Network Cameras:</b> AXIS High PoE midspan 1-port 100-240 VAC, max 60 W recommended <b>AXIS Q6100-E with AXIS Q63-E PTZ Network Cameras:</b> AXIS High PoE midspan 1-port 100-240 VAC, max 60 W recommended, plus AXIS Camera Heater Power Supply (required when used with AXIS Q63-E PTZ Network Camera)
<b>Network protocols</b>	IPv4, IPv6 USGv6, ICMPv4/ICMPv6, HTTP, HTTPS, HTTP/2, TLS, QoS Layer 3 DiffServ, FTP, SFTP, CIFS/SMB, SMTP, mDNS (Bonjour), UPnP®, SNMP v1/v2c/v3 (MIB-II), DNS/DNSv6, DDNS, NTP, NTS, RTSP, RTP, SRTP, TCP, UDP, IGMP, RTCP, ICMP, DHCPv4/v6, ARP, SSH, NTP, LLDP, CDP, MQTT v3.1.1, Secure syslog (RFC 3164/5424, UDP/TCP/TLS), Link-Local address (ZeroConf)	<b>Connectors</b>
<b>System integration</b>		RJ45 10BASE-T/100BASE-TX/1000BASE-T PoE RJ45 10BASE-T/100BASE-TX/1000BASE-T Q61-E port M8 3-pin AC/DC input
<b>Application Programming Interface</b>	Open API for software integration, including VAPIX® and AXIS Camera Application Platform; specifications at <a href="https://axis.com">axis.com</a> One-click cloud connection ONVIF® Profile G, ONVIF® Profile M, ONVIF® Profile S, and ONVIF® Profile T, specification at <a href="https://onvif.org">onvif.org</a>	<b>Storage</b>
<b>Video management systems</b>	Compatible with AXIS Camera Station Edge, AXIS Camera Station Pro, AXIS Camera Station 5, and video management software from Axis' partners available at <a href="https://axis.com/vms">axis.com/vms</a> .	Support for SD/SDHC/SDXC card and encryption Recording to network-attached storage (NAS) For SD card and NAS recommendations see <a href="https://axis.com">axis.com</a>
<b>Analytics</b>	<b>Included</b> Directional audio detection, autopilot, AXIS Motion Guard, AXIS Fence Guard, and AXIS Loitering Guard, AXIS Video Motion Detection, active tampering alarm, edge storage events Support for AXIS Camera Application Platform enabling installation of third-party applications, see <a href="https://axis.com/acap">axis.com/acap</a>	<b>Operating conditions</b>
<b>Event conditions</b>	Analytics, edge storage events, virtual inputs through API Device status: above operating temperature, above or below operating temperature, below operating temperature, fan failure, IP address removed, network lost, new IP address, storage failure, system ready, within operating temperature Edge storage: recording ongoing, storage disruption I/O: manual trigger, virtual input MQTT subscribe PTZ: PTZ ready Scheduled and recurring: scheduled event	-50 °C to 50 °C (-58 °F to 122 °F) with AXIS Camera Heater Power Supply -40 °C to 50 °C (-40 °F to 122 °F) Maximum temperature according to NEMA TS 2 (2.2.7): 74 °C (165 °F) Start-up temperature: -40 °C (-40 °F) Humidity 10–100% RH (condensing)
		<b>Storage conditions</b>
		-40 °C to 65 °C (-40 °F to 149 °F) Humidity 5–95% RH (non-condensing)
		<b>Approvals</b>
		EMC EAC, EN 55032 Class A, EN 55035, EN 50121-4, IEC 62236-4, EN 61000-3-2, EN 61000-3-3, EN 61000-6-1, EN 61000-6-2, FCC Part 15 Subpart B Class A, ICES-3(A)/NMB-3(A), VCCI Class A, RCM AS/NZS CISPR 32 Class A, KC KN32 Class A, KN35 <b>Safety</b> IEC/EN/UL 62368-1, CAN/CSA C22.2 No. 62368-1, IEC/EN/UL 60950-22, CAN/CSA-C22.2 No. 60950-22, IS 13252 <b>Environment</b> IEC 60068-2-1, IEC 60068-2-2, IEC 60068-2-6, IEC 60068-2-14, IEC 60068-2-27, IEC 60068-2-78, IEC/EN 60529 IP66, IEC/EN 62262 IK10, NEMA 250 Type 4X, NEMA TS 2 (2.2.7-2.2.9)

	<b>Network</b> NIST SP500-267		
<b>Dimensions</b>	ø 361 mm (14.2 in) Height: 192 mm (7.6 in)	<b>Optional accessories</b>	Axis Lens M12 6 mm 5P, Axis Lens M12 12 mm 5P, Axis Lens M12 16 mm 5P, Axis Lens M12 25 mm 5P, AXIS T91 Mounting accessories, Axis Midspan 60 W 1-port, AXIS Camera Heater Power Supply For more accessories, see <a href="http://axis.com">axis.com</a>
<b>Weight</b>	4.0 kg (8.8 lb) excluding an AXIS Q61-E PTZ Network Camera or AXIS Q63-E PTZ Network Camera	<b>Languages</b>	English, German, French, Spanish, Italian, Russian, Simplified Chinese, Japanese, Korean, Portuguese, Polish, Traditional Chinese, Dutch, Czech, Swedish, Finnish, Turkish, Thai, Vietnamese
<b>Included accessories</b>	AXIS Q61-E and AXIS Q63-E adapter, bayonet screws, installation guide, Windows® decoder 1-user license	<b>Warranty</b>	5-year warranty, see <a href="http://axis.com/warranty">axis.com/warranty</a>
<b>Required accessories</b>	AXIS Camera Heater Power Supply is required when an AXIS Q63 Series is used.		